

15-7677937	SHARK 2 COMBI-DAB		Rear roof antenna
	AM-FM	DAB-DAB+	
Connector	AM/FM = HC97 F (RAKU 2 F) DAB = SMB F		
Ext. cable	DAB (L = 5 mt Z = 50 Ω C = 101 pF/m) POWER (L = 5 m)		
Power Supply	AM/FM = 12V / 12V Phantom DAB = 12V / 12V Phantom		
Frequency	AM = 0,15 ÷ 1,71 MHz	FM = 87,5 ÷ 108 MHz	III Band = 174 ÷ 240 MHz
Consumption	AM/FM = 50 mA max DAB = 50 mA max		
Mounting	Coachwork drilling OE: square 15x15 mm, r: 2 mm AFT: hole Ø 19 mm		
			Gain III Band = 10 dBi

15-7677940	SHARK 2 TRI-DAB			Rear roof antenna
	AM-FM	DAB-DAB+	GPS	
Connector	AM/FM = HC97 F (RAKU 2 F) DAB = SMB F GPS = SMB F			
Ext. cable	DAB (L = 5 mt Z = 50 Ω C = 101 pF/m) GPS (L = 5 mt Z = 50 Ω C = 100 pF/m) POWER (L = 5 m)			
Power Supply	AM/FM = 12V / 12V Phantom DAB = 12V / 12V Phantom GPS = 3 ÷ 5V Phantom			
Frequency	III Band = 174 ÷ 240 MHz	GPS = 1575,42 ± 1,023 MHz		Gain III Band = 10 dBi GPS ≥ 27 dBi
Consumption	AM/FM = 50 mA max DAB = 50 mA max GPS = 30 mA max			
Mounting	Coachwork drilling OE: square 15x15 mm, r: 2 mm AFT: hole Ø 19 mm			

15-7677942	SHARK 2 DAB		Rear roof antenna
	DAB-DAB+		
Connector	SMB F	Ext. cable	L = 5 mt Z = 50 Ω C = 101 pF/m) POWER: L = 5 m
Power Supply	DAB = 12V / 12V Phantom	Frequency	III Band = 174 ÷ 240 MHz Gain III Band = 10 dBi
Consumption	DAB = 50 mA max	Mounting	Coachwork drilling OE: square 15x15 mm, r: 2 mm AFT: hole Ø 19 mm

